



ITEM	MATERIAL	UC1R QTY	UC1AR QTY	ITEM	MATERIAL	UC1R QTY	UC1AR QTY
c	Bolts, Machine 5/8" X 10"	4	4	cj2	Wire, #2 Ground Insulated	6'	
d	Washer; Curved, 3"X3"X11/16"	4	4	cj2	Wire, 2/0 Ground Insulated		6'
d1	Washer, Square, 2" X 2"	1	1	ek	Locknut 5/8"	5	5
g	Crossarm. Fiberglass 8'	2	2	ugc	Cable Riser Shield/Power Mold	2	2
o	Bolt, Eye 5/8"	1	1	ugk	Primary Terminator	3	3
p	Cu Crimps #6	3	3	uhc	MB4 Terminator Bracket, (UC1R)	3	
ae	Arrester, Surge 18kV	3	3	uhc	MB5 Terminator Bracket, (UC1AR)		3
af	Cutout Loadbreak	3	3	uhc1	Grip, Kellum	3	3
ap	Clamp, Hot Line	3	3	uhj	Bracket, Crossarm Mounting	6	6
ap1	Baskets, Hot Line	3	3	rp1	Bird Guard 36"	4	4
av	Wire, #2 Insulated Tap	30'		rp2	Bird Guard 24"	2	2
av	Wire, 2/0 Insulated Tap		30'	rp11	Loadbreak Cover	3	3
bo	Shackle, Anchor	1	1	rp12	Arrester Cover	3	3
cj	Wire, #6 Insulated Green Ground	20'	20'	rp14	Terminator Cover	3	3

- NOTES:
1. Move neutral when required.
 2. The concentric neutral and the arrester ground shall be installed so they do not touch the mounting bracket.
 3. Trim the stem connector so that it does not protrude from the terminator cover.
 4. Terminator cover shall be installed over the first skirt of the terminator.
 5. Call out UC1R for 1/0 EPR Conductor.
 6. Call out UC1AR for 4/0 EPR Conductor.

Three Phase Cable Terminal Pole

RUS
06/02/14
REV. A



UC1R
UC1AR