



Note:

1. When tapping center phase, install post type insulator, "VA1.011P", horizontally on crossarm 24" from center of pole and fasten insulated jumper to insulator.

ITEM	NO.	MATERIAL	ITEM	NO.	MATERIAL
d3	2	Washer, curved 3" x 3" x 11/16"	s	1	Clevis, swinging
k	1	Insulator, polymer distribution deadend	cm	1	Insulator, spool - 3"
l	1	Clamp deadend	eu	1	Link, extension fiberglass
o	2	Bolt, oval eye, 5/8" x req'd length	ek	2	Locknuts

DESIGN PARAMETERS:

Allowable Longitudinal Load Equals Lesser of:
5,000 lbs/conductor or manufacturer's specifications

**24.9 / 14.4 KV, 3-PHASE
SINGLE PHASE TAP GUIDE
SMALL CONDUCTORS**

06/13/08

Rev. 0



VC5.11GR