



ITEM	PART #	MATERIAL	QTY	ITEM	PART #	MATERIAL	QTY
c	9373	Machine, Bolt 3/4"	2	av	3114	Jumper, Stranded Insulated	40'
d	9093	Washer, Curved 3"X3"X 3/4"	2	be		Recloser, Electronic (14.4kV)	3
g	2075	OCR Bracket 3SPR-8 Aluma-Form	1	cj	3011	#6 UV Jacket GRN STR Cu	22'
p	9027	Crimp	1	ek	9097	Locknut, 3/4"	2
t		Control Box	1	sj	7126	Switch, Bypass Disconnect (25kV)	3
ae	80	Arrestor, Surge (18kV)	6	rp	4705	Transformer Bushing Cover, Small	1
an		Transformer, 1kVA 14.4kV/120V	1	rp	4708	Transformer Bushing Cover, Large	6
ap	2140	Clamp, Hot Line	12	rp	4720	Arrestor Cover	6
ap	2147	Hot Line Stirrup	9				

- Notes:
1. The recloser terminal bushing connected directly to the coil should be connected to the source.
  2. Each recloser tank shall have two connections to ground.
  3. the primary bushing cover on the recloser bushing is only to cover the first skirt of the bushing.
  4. Clearances shall be maintained for ground clearance to live equipment as specified by NESC or the staking guide line, whichever is greater.
  5. VR3.3R is to be installed on VC6.51R(G)
  6. Ground control box to pole ground with "cj" and "p"

**3 PHASE ELECTRONIC RECLOSER  
WITH BYPASS SWITCH  
14.4/24.9kV**

RUS		<b>VR3.3R</b>
3/22/2016		
Rev. B		