



ITEM	MATERIAL	UA1AR	UA1BR	Part#	ITEM	MATERIAL	UA1AR	UA1BR	Part#
		QTY	QTY				QTY	QTY	
av	Wire, 2/0 tap wire, as req'd		15'	3115	uhc	MB4 Terminator Bracket(UA1AR)	1		9430
d	Washer, Square 2 x 2	5	5	9091	uhc	MB5 Terminator Bracket(UA1BR)		1	9433
c	Bolt, Machine 5/8" x 10"	4	4	9372-14	ab	Bracket / (holder for MB5,MB4)	1	1	2045
ugk	Primary Terminators	1	1	8150	rp12	Arrestor Bird Cover	1	1	9227
p	#6 cu crimpet	1	1	9027	rp11	Bird Switch Cover	1	1	9241
af	Cutout combo	1	1	4171	ek	Locknuts	5	5	9096
ap	Clamp, hot line	1	1	2142	cj	Wire, #6 insulated Green Ground, as req'd	30'	30'	3011
ugc1	Cable riser shield /Power mold 4"or 6"	2	2	8250	ap	Baskets, hot line	1	1	2142
uhj	Fiber glass arm bracket	1	1	8524	av1	Wire, #2 insulated tapwire	15'		3114
uhc	Kellum Grip	1	1	9221	bo	Anchor Shackle	1	1	7080
dg	Eye Bolt	1	1	9368					

- NOTES:
1. Total arrester lead length must be under 3'.
  2. No bends permitted in cable within 6" of terminal base.
  3. All live parts must have an 18-foot clearance above ground and must be installed a minimum of 6 inches above the neutral conductor.
  4. Bracket to be set to align w/cutout
  5. Use MB-4 for 1/0 EPR (UA1AR)
  6. Use MB-5 for 4/0 EPR (UA1BR)
  7. Please refer to Tying Guide.
  8. Concentric neutral needs to be covered.

SINGLE-PHASE CABLE DEADEND  
TERMINAL POLE

RUS  
01/19/12  
Rev. 0



UA1AR  
UA1BR